



OUTPUT:
3-4.5-6-7.5-
9-12V / 2000mA

- C1: 0.1uF/275V AC CAP
- C2: 0.001uF/275V AC CAP
- C3: 47uF/400V CAPACITOR
- C4: 47uF/25V CAPACITOR
- C5: 0.1uF/50V CAP
- C6: 2.2nF/250V Y1 TYPE CAP
- C7: 0.1uF/50V CAP
- C8: 1000uF/25V CAP
- C9 C10: 0.01uF/25V CAP
- C11: 220uF/16V CAP
- C12: 470pF/1000V CAP
- C13: 0.01uF/1000V CAP
- C14: 0.01uF/50V CAP
- R1: 5.9 OHM 0.25W
- R2: 18 OHM 0.25W
- R3: 220 OHM 0.25W
- R4: 100K OHM 1W
- R5: 8 OHM 0.25W

- R6: 100 OHM 0.25W
- R7: 10K OHM 0.25W
- R8: 5.1K OHM 0.25W
- R9: 1K OHM 0.25W
- R10: 270 OHM 0.25W
- R11: 400 OHM 0.25W
- R12: 525 OHM 0.25W
- R13: 790 OHM 0.25W
- R14: 1.53K OHM 0.25W
- R15: 10K OHM 0.25W
- D1-D4: IN4007 DIODE
- D5 D7: UF4005 DIODE
- D6: P6KE200 ZENER
- D8: SB850 DIODE

- FUSE: 250V 800mA FUSE
- LED: 3mm RED LED
- TF: TRANSFORMER
- BR1: 22mH 400mA
- BR2: 150uH/2.5A
- L1 L2: 220uH 400mA
- L3: 3.3uH 2A
- IC1: TOP225Y
- IC2: LTV817A
- IC3: S431Z
- SW: VOLTAGE CHANGE SWITCH

Title			MW7C20TGS		
Size	Number			Revision	B
A4				Sheet of	Michael jiang
Date:	21-Jan-2003			Drawn By:	
File:	H:\usr\jw\SCH\7c20-11\7c20-CEI.sch				